

» PAS-8-S8M4

PA System with Active sub-woofer & 4-Channel active microphone mixer with audio amplifier

- A high-performance ultra-compact line-array speaker featuring a wide and uniform horizontal dispersion with constant vertical beam-width and long throw distance: PHA-8
- Compact, high-efficiency front-firing, active sub-woofer: PSUB-81
- A 4-Channel active microphone mixer with built-in high-performance digital audio power amplifier: PMA-4
- Quick and easy set-up and intuitive operation
- Built-in high-capacity rechargeable battery for 12+ hours of normal use
- Compact size, rugged construction, fully self-contained design
- Ideal solution for portable PA system or fixed installations
- Speaker can be used with other high-powered amplifiers
- Treble and Bass Control

Applications:

Fixed install PA Systems, Gymnasiums, Sports courts, Dance studios, health and fitness clubs, cafeterias, Portable PA Systems, Class-room audio solutions, Conference rooms, Solo/Duet Singers, Acoustic Guitar players, Mobile DJ, Lecturers, Small group seminars, Singer/song writers, Hotel meeting rooms, Hotels, Restaurants, Street performers, Magicians, etc.



TO PLACE an ORDER or for QUESTIONS,
Emails Us: sales@pragmatic1.com, Call Us: (408) 748-1100 or Fax Us: (408) 663-9783

PHA-8 speaker



- RELATED PRODUCTS**
- PAS*Port™ complete portable Public Address system
 - PHA (ultra compact line-array speakers)
 - MBA-148 Mono - amplifier
 - PSUB-12 sub-woofer
 - PWM Wireless microphones
 - PreAmp9 - Compact audio preamplifier with 9 dB gain

LINE-ARRAY SPEAKER	8 High-performance full-range drivers (75 Watts max)
ACTIVE SUB-WOOFER	8" dual-voice coils, front-firing, ported, variable cross-over
MICROPHONE PRE-AMPLIFIER	Ultra low noise, wide-dynamic range
MICROPHONE INPUTS	2 high-gain, 1 medium gain
LINE LEVEL INPUTS	1 line-level input with variable gain
INPUT IMPEDANCE	20K Ohms
MICROPHONE INPUT	Un-balanced TRS Phono jack
FREQUENCY RESPONSE	Sub-woofer (33 Hz - 150 Hz), Line array (120 Hz - 20 KHz)
SPEAKER IMPEDANCE	4 Ohms
POWER	DC 15V (16.5V max) mixer-preamp, Sub-woofer
OPERATING CONDITIONS	Temperature 50°-104°F (10°-40°C), Humidity 20-85% (non-condensing)
DIMENSIONS (HxWxD)	18"x2"x2" (Line-array), 12"x12"x13" (Sub-woofer), 10"x5"x2" mixer
WEIGHT	7.5 lb with rechargeable internal battery pack, excludes subwoofer
POWER SUPPLY REGULATIONS	UL, cUL, FCC (Class A/B), TUV, CCC, CE, CISPR, RoHS
PACKAGE CONTENTS	Microphone mixer/power amplifier, AC/DC adapter
WARRANTY	One year limited warranty on parts and labor

PMA-4 4-channel active mixer with audio power amplifier



Complete system fully self-contained in a simple soft carrying bag



TO PLACE an ORDER or for QUESTIONS,
Emails Us: sales@pragmatic1..com, Call Us: (408) 748-1100 or Fax Us: (408) 663-9783